



## Inverter Remote Control

⚡ Pure Sine Wave

Model  
S-R8

### Design Features

- Designed for use with the following Samlex Pure Sine Wave Inverters:
  - SA-1000K-112
  - SA-1000K-124
  - SA-2000K-112
  - SA-2000K-124
  - SA-3000K-112
  - SA-3000K-124
- Push button system on/off
- LED indicator for remote override and ignition lockout
- 25 feet of wire included

## 2 YEAR WARRANTY

MODEL NO.	S-R8
INPUT VOLTAGE RANGE	10.5 – 60 VDC based on the battery input voltage of the inverter (can be used for 12V, 24V & 48V inverters)
OPERATING TEMPERATURE RANGE	0 - 40°C
STORAGE TEMPERATURE RANGE	- 30°C to + 70°C
STAND-BY CURRENT DRAW	< 40 mA
DIMENSIONS, INCHES (L x W)	2.8 x 2.1
DIMENSIONS, MM (L x W)	70 x 53.5
APPLICABLE MODELS	SA-1000K, 2000K, 3000K Series

NOTE: Specifications are subject to change without notice